

# BG-3GS14

SDI 1x4 Splitter

## User Manual







## TABLE OF CONTENTS

Statement	4
Safety Precaution	4
Introduction	5
Features	5
Packing List	5
Specifications	6
Connection and Operation	7
Application Example	7
Tech Support	8
Limited Product Warranty Terms	8
Mission Statement	8
Copyright	8



## Statement

---

Please read these instructions carefully before connecting, operating, or configuring this product. Please save this manual for future reference.

## Safety Precaution

---

- To prevent damaging this product, avoid heavy pressure, strong vibration, or immersion during transportation, storage, and installation.
- The housing of this product is made of organic materials. Do not expose to any liquid, gas, or solids which may corrode the shell.
- Do not expose the product to rain or moisture.
- To prevent the risk of electric shock, do not open the case. Installation and maintenance should only be carried out by qualified technicians.
- Do not use the product beyond the specified temperature, humidity, or power supply specifications.
- This product does not contain parts that can be maintained or repaired by users. Damage caused by dismantling the product without authorization from BZBGear is not covered under the warranty policy.
- Installation and use of this product must strictly comply with local electrical safety standards.



## Introduction

---

The BG-3GS14 is a 1x4 3G-SDI splitter that splits one SDI input to four SDI outputs simultaneously. With a signal rellocking feature, the unit also extends a video signal for long distances. This reliable and powerful tool provides consistent connections in a variety of different scenarios such as adding multiple outputs for monitoring a video feed on separate displays, splitting a signal and cascading multiple displays for large video distribution systems, or just to extend an SDI signal. The BG-3GS14 supports multiple resolutions up to 1080p@60 as well as multiple color spaces such as RGB or YCbCr 4:4:4.

## Features

---

- This product is designed with an equalizer IC in its input and a drive IC in its outputs. This allows all inputs and outputs to support long coaxial cables while still maintaining quality signal (3G: 80m/263ft, HD: 120m/394ft, SD: 200m/656ft).
- **Multiple video resolutions :**
  - 3G 1080p @50/60
  - HD 1080p @24/25/30
  - HD 1080i @50/60
  - HD 720p @24/25/30/50/60
  - SD 480i, 576i and 625i
- **Supports multiple color space :**
  - RGB or YCbCr 4:4:4 sampled
  - YCbCr 4:2:2 or 4:2:0 sampled
  - Data rates: 270Mbps~2.97Gbps
  - Deep color: 8bit, 10bit, 12bit.

## Packing List

---

- 1 x BG-3GS14 SDI 1x4 Splitter
- 1 x Power adapter 5V@2A
- 1 x User Manual



## Specifications

<b>Signal Input/Output</b>	
Input Connector	1x SDI BNC Male
Output Connector	4x SDI BNC Male
<b>SDI Cable Distance (RG59 cable)</b>	
3G Mode	Up to 80m (263ft)
HD Mode	Up to 120m (394ft)
SD Mode	Up to 200m (656ft)
<b>Mechanical</b>	
Size(L-W-H)	155×86×23.5 mm (6.1 x 3.4 x 0.93 in)
Weight (Net)	266 g (9.4 oz)
<b>Environmental</b>	
Operating Temperature	0 °C to +70°C (32°F to 158°F)
Operating Humidity	10% to 85 % RH (no condensation)
Storage Temperature	-10°C to +80°C (14°F to 176°F)
Storage Humidity	5% to 90 % RH (no condensation)
<b>Power Requirement</b>	
External Power Supply	5V DC@ 2A
Power consumption (Max)	1.2W
<b>Regulatory Approvals</b>	
Converter Unit	FCC,CE,UL
Power Supply	UL,CE,FCC
<b>Accessories Adapter</b>	
User Manual	English version





## Tech Support

---

Have technical questions? We may have answered them already!

Please visit BZBGear's support page ([bzbgear.com/support](https://bzbgear.com/support)) for helpful information and tips regarding our products. Here you will find our Knowledge Base ([bzbgear.com/knowledge-base](https://bzbgear.com/knowledge-base)) with detailed tutorials, quick start guides, and step-by-step troubleshooting instructions. Or explore our YouTube channel, BZB TV ([youtube.com/c/BZBTVchannel](https://youtube.com/c/BZBTVchannel)), for help setting up, configuring, and other helpful how-to videos about our gear.

Need more in-depth support? Connect with one of our technical specialists directly:

<b>Phone</b>	<b>Email</b>	<b>Live Chat</b>
1.888.499.9906	support@bzbgear.com	bzbgear.com

## Limited Product Warranty Terms

---

Pro Line: 5-year warranty from the date of purchase for AV/Broadcasting products bought on or after August 1, 2024.

Essential Line: 3-year warranty from the date of purchase for AV/Broadcasting products bought on or after August 1, 2024.

Cables: Lifetime Limited Product Warranty.

For complete warranty information, please visit [bzbgear.com/warranty](https://bzbgear.com/warranty).

For questions, please call 1.888.499.9906 or email support@bzbgear.com.

## Mission Statement

---

BZBGear is a breakthrough manufacturer of high-quality, innovative audiovisual equipment ranging from AVoIP, professional broadcasting, conferencing, home theater, to live streaming solutions. We pride ourselves on unparalleled customer support and services. Our team offers system design consultation, and highly reviewed technical support for all the products in our catalog. BZBGear delivers quality products designed with users in mind.

## Copyright

---

All the contents in this manual and its copyright are owned by BZBGear. No one is allowed to imitate, copy, or translate this manual without BZBGear's permission. This manual contains no guarantee, standpoint expression or other implies in any form. Product specification and information in this manual is for reference only and subject to change without notice.

**All rights reserved.** No reproducing is allowed without acknowledgement.